

Order at 訂貨熱線:

香港批發/分銷 T(852) 2781 2855 澳門批發/分銷 T(853) 2822 2751 工程/商業項目 T(852) 2691 9166

E enquiry@supermoon.hk www.supermoon.hk

SINAMICS G120P

The energy-efficient, user-friendly frequency inverter for pumps, fans, and compressors

Brochure · November 2009



SINAMICS Drives

Answers for industry.

SIEMENS

SINAMICS G120P

The modular frequency inverter for pumps, fans, and compressors

Ideal for building automation, water and process industries

The SINAMICS G120P frequency inverter is a cost-effective, efficient, and easy-to-operate pump, fan, and compressor drive featuring a wide range of functions.

It has been specially designed for the industrial environment as well as for applications in heating, ventilation, and air-conditioning.

The new SINAMICS G120P frequency inverter is the perfect solution for applications, such as closed-loop speed control for ventilation fans, circulating pumps for heating and cooling systems, booster pumps, or pumps for level control.

SINAMICS G120P offers a high degree of user-friendliness:

- Integrated application-specific wizards and macros for simple commissioning
- USB port and IOP operator panel with clear-text display (IOP = Intelligent Operator Panel)
- Modular design comprising of a Control Unit, Power Module, and operator panel or blanking plate

SINAMICS G120P supports functions for leveraging energy efficiency across the entire process chain:

- Minimum apparent power loss thanks to efficient technology
- Automatic adaptation of the motor current to prevailing load conditions with ECO mode
- Hibernation (sleep mode) as a function of the setpoints
- Automatic switchover to mains operation at rated speed
- Auto-ramping function for current limitation purposes

The technology reduces line harmonic distortions and ensures compliance with the relevant standards without the need for additional components.



Highlights

Mechanical system

- High degree of protection IP55/UL type 12
- Efficient, modular frequency inverter
- Reliable operation in harsh environments, e.g. suitable for ambient temperatures up to +60 °C

Flectronics

- Wide range of PFC functions integrated
- Comprehensive monitoring functions
- PLC functions for local control tasks
- Reduced line harmonic distortions and compliance with relevant standards
- Energy savings across the entire process chain
- Easy-to-operate via wizards

Integrated communication

 USS, Modbus RTU, BacNet MS/TP, PROFIBUS DP, CANopen






SINAMICS G120P belongs to the SINAMICS drive family of innovative, future-oriented drive solutions

- Broad range of power ratings from 0.12 kW to 120 MW
- Low-voltage and medium-voltage versions available
- Seamless, integrated functionality by using common hardware and software platforms
- Common engineering and configuration tools
 - SIZER for engineering
 - STARTER for configuration and commissioning
- High degree of flexibility and ability to be combined

Whatever the drive task, SINAMICS has the optimum drive – and they can all be engineered, parameterized, commissioned, and operated in the same way.



SINAMICS G120P

Innovation for central drive technology

	Function	Benefits		
Optimum energy mar	nagement through innovative technology			
	Optimized architecture	Reduced line harmonic distortions No reactors \rightarrow Compact design Lower apparent power \rightarrow Smaller cable cross-sections Limits for harmonic currents and THD compliant with IEC/EN 61000-3-12 without the need for additional measures ($R_{\text{Sce}} \ge 120$)		
	Dual rating (LO/HO)	Optimum load factor for pump/fan/compressor applications		
	V/f (ECO) motor control	Energy-saving capability through automatic adaptation of the motor current to prevailing load conditions (lower motor losses under partial load conditions)		
	Hibernation mode	Energy-saving capability because the drive is started/stopped in line with the current setpoints, thereby avoiding excessive mechanical loads		
Straightforward, appl	ication-specific commissioning and operation			
	Integrated USB port	Simple commissioning/diagnostic routine with PC tools and standardized cable		
	IOP interface (Intelligent Operator Panel)	Wizard-based, user-friendly operator panel		
	Remote maintenance/diagnostics and parameterization	Simplified, central commissioning/maintenance Reduced costs as service personnel assignments are no longer required		
	Slot for micro memory card (MMC)	Data back-up for easy replacement		
Flexible deployment of integrated functions				
	PLC functions for local control tasks	Flexible deployment of integrated functions → No need for additional, external components		
	4 integrated, freely-programmable PID controllers	Distributed closed-loop control for motor-independent process control without PLC		
	3 freely-programmable digital time switches	Control for freely-selectable daily and weekly programs		
Flexible deployment	across a wide range of applications			
	Isolated digital inputs with separate voltage classification Insulated analog inputs	Protection against erroneous voltage EMC-compliant design without the need for additional components in line with process industry requirements		
	NI1000/PT1000 temperature sensor interface	Direct connection of temperature sensors without external interface		
	230 V relay	Direct control for auxiliary equipment, e.g. reactor or valve actuators		
Flexible, modular system for challenging environmental conditions				
	Can be deployed at ambient temperatures up to +60 °C (140 °F) thanks to sophisticated ventilation system	Suitable for use in harsh environments		
	Removable operator panel	Protection against unauthorized access Degree of protection IP54 with operator panel, IP55 with blanking plate; UL type 12		
	Modular design of power and control electronics	Simply plug on Control Unit to re-commission Power range can be easily extended Fast replacement of power units		

SINAMICS G120P

Technical data

Mechanical data				
Mounting dimensions (W x H x D) • Size FSA • Size FSB • Size FSC	154 x 460 x 264 mm (6.06 x 18.11 x 10.39 in) 180 x 540 x 264 mm (7.09 x 21.26 x 10.39 in) 230 x 620 x 264 mm (9.06 x 24.41 x 10.39 in)			
Degree of protection • With operator panel • With blanking plate	IP54/UL type 12 IP55/UL type 12			
Electrical data				
Power rating (low overload LO)	0.37 18.5 kW (0.5 25 hp)			
Line supply voltage	380 480 V 3 AC ±10 %			
Line frequency	47 63 Hz			
Overload capability (low overload LO)	 1.5 x rated output current (150 %) for 3 s every 300 s 1.1 x rated output current (110 %) for 57 s every 300 s 			
Rated input current (at 40 °C (104 °F))	1.7 53 A			
Rated output current (at 40 °C (104 °F))	1.3 45 A			
Operating temperature	up to +60 °C (140 °F) with derating			
Relative humidity	< 95 % RH, non-condensing			
Output frequency	0 200 Hz			
Pulse frequency	4 kHz (default) The pulse frequency can be changed manually in 2 kHz steps.			
Skip frequency range	4, parameterizable			
Fixed frequencies	16, programmable			
Digital inputs and outputs	 6 DI, 3 DO, 4 AI, 2 AO 1 x KTY/PTC/ThermoClick sensor 2 x PSU-out (10 V DC, 24 V DC) 1 x PSU-in (24 V DC) 			
Communication				
Bus interface	Control Unit CU230P-2 supports a wide range of communications protocols, e.g. USS, Modbus RTU, BacNet MS/TP, PROFIBUS DP, CANopen			
Software				
Commissioning tool	 STARTER for commissioning via PC IOP (Intelligent Operator Panel) 			

Open-loop/ closed-loop control technique Operating functions - Vif (linear, square-law, FCC, ECO) - Vector control without encoder (SLVC) - Vector control without encoder (SLVC) - Automatic restart (after power failure) - Energy saving mode (ECO mode) - Hibernation (sleep mode, to start and stop the motor depending on demand) - Flying restart (switch on inverter when motor is turning) - Motor staging (for applications that require 1-4 motors depending on the flow rate, for example) - 4 PID technology controllers (e.g. to control pressure, level, flow rates) - Logical and arithmetic functions that use function blocks - Emergency operation/Essential services mode (to operate the motor as long as possible in the event of an emergency) - Multi-zone controller (to control the temperature in several rooms simultaneously using setpoint/actual value comparisons) - Bypass Protective functions Motor temperature monitoring with and without temperature sensor (via PTC, KTY and ThermoClick sensor) - Overcurrent protection - Load torque monitoring - Overvoltage protection (V _{DCmax} controller) Braking functions DC braking Motors that can be connected Standards Standards Standards Standards Standards Standards Standards (Integrated line filter for installation to EN 61800-3 C2 (class A) and EN 61800-3 C2 (class A) and EN 61800-3 C1 (class B) Accessories - Blanking plate (if no panel is required) - MMC for Control Unit - PC connecting cable RS232 and USB - Mounting kit	Technology functions			
(after power failure) • Energy saving mode (ECO mode) • Hibernation (sleep mode, to start and stop the motor depending on demand) • Flying restart (switch on inverter when motor is turning) • Motor staging (for applications that require 1-4 motors depending on the flow rate, for example) • 4 PID technology controllers (e.g. to control pressure, level, flow rates) • Logical and arithmetic functions that use function blocks • Emergency operation/Essential services mode (to operate the motor as long as possible in the event of an emergency) • Multi-zone controller (to control the temperature in several rooms simultaneously using setpoint/actual value comparisons) • Bypass Protective functions Motor temperature monitoring with and without temperature sensor (via PTC, KTY and ThermoClick sensor) • Overcurrent protection • Load torque monitoring • Overvoltage protection (V _{DCmax} controller) Braking functions DC braking Motors that can be connected Standards Standards Standards Standards Conformance Electromagnetic compatibility Integrated line filter for installation to EN 61800-3 C2 (class A) and EN 61800-3 C1 (class B) Accessories • Blanking plate (if no panel is required) • MMC for Control Unit • PC connecting cable RS232 and USB	closed-loop control	•		
with and without temperature sensor (via PTC, KTY and ThermoClick sensor) Overcurrent protection Load torque monitoring Overvoltage protection (V _{DCmax} controller) Braking functions DC braking 3-phase synchronous and induction motors Standards Standards Standards UL, CE, c-tick, cUL, CSA Electromagnetic compatibility Integrated line filter for installation to EN 61800-3 C2 (class A) and EN 61800-3 C1 (class B) Accessories Blanking plate (if no panel is required) MMC for Control Unit PC connecting cable RS232 and USB	Operating functions	 (after power failure) Energy saving mode (ECO mode) Hibernation (sleep mode, to start and stop the motor depending on demand) Flying restart (switch on inverter when motor is turning) Motor staging (for applications that require 1-4 motors depending on the flow rate, for example) 4 PID technology controllers (e.g. to control pressure, level, flow rates) Logical and arithmetic functions that use function blocks Emergency operation/Essential services mode (to operate the motor as long as possible in the event of an emergency) Multi-zone controller (to control the temperature in several rooms simultaneously using setpoint/actual value comparisons) 		
Motors that can be connected Standards Standards Standards onformance Electromagnetic compatibility Compatibility Description Blanking plate (if no panel is required) MMC for Control Unit PC connecting cable RS232 and USB	Protective functions	with and without temperature sensor (via PTC, KTY and ThermoClick sensor) Overcurrent protection Load torque monitoring		
can be connected Standards Standards conformance Electromagnetic compatibility EN 61800-3 C2 (class A) and EN 61800-3 C1 (class B) Accessories Blanking plate (if no panel is required) MMC for Control Unit PC connecting cable RS232 and USB	Braking functions	DC braking		
Standards conformance Electromagnetic compatibility Integrated line filter for installation to EN 61800-3 C2 (class A) and EN 61800-3 C1 (class B) Accessories Blanking plate (if no panel is required) MMC for Control Unit PC connecting cable RS232 and USB		3-phase synchronous and induction motors		
Electromagnetic compatibility Integrated line filter for installation to EN 61800-3 C2 (class A) and EN 61800-3 C1 (class B) Accessories Blanking plate (if no panel is required) MMC for Control Unit PC connecting cable RS232 and USB	Standards			
compatibility to EN 61800-3 C2 (class A) and EN 61800-3 C1 (class B) Accessories Blanking plate (if no panel is required) MMC for Control Unit PC connecting cable RS232 and USB	Standards conformance	UL, CE, c-tick, cUL, CSA		
 Blanking plate (if no panel is required) MMC for Control Unit PC connecting cable RS232 and USB 		to EN 61800-3 C2 (class A)		
MMC for Control UnitPC connecting cable RS232 and USB	Accessories			
		 MMC for Control Unit PC connecting cable RS232 and USB		

Siemens AG Industry Sector Drive Technologies Division Subject to change without prior notice Order No.: 6ZB5471-0AR02-0BA0 3P.8222.75.05 / Dispo 18404 BR 1109 3.0 VOG 4 En Printed in Germany © Siemens AG 2009 The information provided in this brochure contains descriptions or characteristics of performance, which in case of actual use do not always apply as described or which may change as a result of further development of the products.

An obligation to provide the respective characteristics shall only exist if expressly agreed in the terms of contract.

Availability and technical specifications are subject to change without prior notice.

All product designations may be trademarks or product names of Siemens AG or supplier companies whose use by third parties for their own purposes could violate the rights of the owners.